

1.Application

CJX2-F AC contactor is suitable for using in the circuits up to the rated voltage 380V AC 50/ 60Hz, current 800A, for long distance breaking circuit and frequently starting or controlling the motor. It also can be used for the control of distribution circuits of rated current from 115A to 800A. It conforms to IEC60947-4-1.

2.Specification

Type	Rated operational current in AC-3(A)	Max power ratings of 3-phase motors in category AC-3(kW)							Operating frequency (time/hour) AC-3	Electrical life AC-3 x10 ⁴	Mechanical life x10 ⁴
		220V 230V	380V 400V	415V	440V	500V	660V 690V	1000V			
CJX2-F115	115	30	55	59	59	75	80	65	1200	120	1000
CJX2-F1154	115	30	55	59	59	75	80	65	1200	120	1000
CJX2-F150	150	40	75	80	80	90	100	65	1200	120	1000
CJX2-F1504	150	40	75	80	80	90	100	65	1200	120	1000
CJX2-F185	185	55	90	100	100	110	110	100	600	100	600
CJX2-F1854	185	55	90	100	100	110	110	100	600	100	600
CJX2-F225	225	63	110	110	110	130	129	100	600	100	600
CJX2-F2254	225	63	110	110	110	130	129	100	600	100	600
CJX2-F265	265	75	132	140	140	160	160	147	600	80	600
CJX2-F2654	265	75	132	140	140	160	160	147	600	80	600
CJX2-F330	330	100	160	180	200	200	220	160	600	80	600
CJX2-F3304	330	100	160	180	200	200	220	160	600	80	600
CJX2-F400	400	110	200	220	250	257	280	185	600	80	600
CJX2-F4004	400	110	200	220	250	257	280	185	600	80	600
CJX2-F500	500	147	250	280	295	355	335	335	600	80	600
CJX2-F5004	500	147	250	280	295	355	335	335	600	80	600
CJX2-F630	630	200	335	375	400	400	450	450	600	80	600
CJX2-F6304	630	200	335	375	400	400	450	450	600	80	600
CJX2-F780	780	220	400	425	425	450	475	40	600	80	600
CJX2-F7804	780	220	400	425	425	450	475	450	600	80	600
CJX2-F800	800	250	450	450	450	450	470	450	600	80	600



CJX2-F5004



CJX2-F630



CJX2-F115



CJX2-F150

Connection/Timing Charts:

CONNECTIONS/TIMING CHARTS

