

1. Application

The product is suitable to be used in circuit of rated voltage up to AC 660V 50/60Hz, rated current from 0.1A to 63A. It is applicable for protection of overload & short circuit of 3 phase squirrel-cage motors. It also can be used as direct starter to start the motor and a switch for changeover the circuit under normal conditions.

2. Specification

DZ208-13			DZ208-16		
Current setting range (A)	Power of controlled motor (KW)	Current rated (A)	Current setting range (A)	Power of controlled motor (KW)	Current rated (A)
0.1-0.16		0.16	1-1.6	0.37/0.55	1.6
0.16-0.24	0.06	0.24	1.6-2.4	0.75	2.4
0.24-0.4	0.09/0.12	0.4	2.4-4	1.1/1.5	4
0.4-0.6	0.12/0.18	0.6	4-6	2.2	6
0.6-1	0.25	1	6-10	3/4	10
1-1.6	0.37/0.55	1.6	10-16	5.5/7.5	16
1.6-2.4	0.75	2.4	16-25	11	25
2-3.2	1.1	3.2	22-23	15	32
2.4-4	1.1/1.5	4	28-40	18.5	40
3.2-5	1.5/2.2	5	36-52	22	52
4-6	2.2	6	45-63	-	63
5-8	3	8			
6-10	3/4	10			
8-13	4/4.5	13			
10-16	7.5	16			
14-20	7.5	20			
18-25	11	25			

3. Dimension

