

1. Application

CJX2-N mechanical interlocking contactor is suitable for using in the circuits up to the rated voltage 660V AC 50Hz, current 620A, for convertible controlling the motor. This mechanical interlocking device ensures contact changeover of the two convertible contactors. It conforms to IEC60947-4-1.

2. Specification



Type	Rated current AC-3(A)	Controlled power (KW)				
		220V	380V	415V	440V	660V
CJX2-09N	9	2.2	4	4	4	5.5
CJX2-12N	12	5.5	5.5	5.5	5.5	7.5
CJX2-18N	18	7.5	7.5	9	9	10
CJX2-25N	25	5.5	11	11	11	15
CJX2-32N	32	7.5	15	15	15	18.5
CJX2-40N	40	18.5	18.5	22	22	30
CJX2-50N	50	15	22	25	30	33
CJX2-65N	63	18.5	30	37	37	37
CJX2-80N	80	22	37	45	45	45
CJX2-95N	95	22	45	45	45	41
CJX2-115N	115	30	55	59	59	80
CJX2-150N	150	40	75	80	80	100
CJX2-170N	170	55	90	100	100	110
CJX2-205N	205	63	110	110	110	129
CJX2-245N	245	75	132	132	132	160
CJX2-300N	300	100	160	200	200	220
CJX2-410N	410	110	220	250	250	280
CJX2-475N	475	147	265	280	280	355
CJX2-620N	620	200	335	400	400	450

Type	Number of Poles	Rated Current AC-3(A)	Rated Current In/A	Controlled power(KW)	
				220V	380V
CJX2-F115N	3P	115	250	200	55
CJX2-F1154N	4P	115	250	200	55
CJX2-F150N	3P	150	355	250	75
CJX2-F1504N	4P	150	355	250	75
CJX2-F185N	3P	185	425	275	90
CJX2-F1854N	4P	185	425	275	90
CJX2-F225N	3P	225	500	315	110
CJX2-F2254N	4P	225	500	315	110
CJX2-F265N	3P	265	630	350	132
CJX2-F2654N	4P	265	630	350	132
CJX2-F330N	3P	330	800	400	160
CJX2-F3304N	4P	330	800	400	160
CJX2-F400N	3P	400	800	500	200
CJX2-F4004N	4P	400	800	500	200
CJX2-F500N	3P	500	1000	700	250
CJX2-F5004N	4P	500	1000	700	250
CJX2-F630N	3P	630	1250	1000	335
CJX2-F6304N	4P	630	1250	1000	335
CJX2-F800N	3P	800	1250	1000	400