

1. Application

Qs5 cam starter is mainly used to start forward or backward and stop directly three-phase asynchronous electric motor with AC 50/60Hz, voltage up to 500V and capacity up to 7.5KW. It can also be used for changeover from one ind of circuit to the other.

2.Specification

Model	Mark	Rated current (A)	Motor control capacity (HP)	Mechanical life (times)	Frequency of operation (per hr)	Applications	Position of lever
QS5-15A	I-O	15	5.5	250000	200	ON-OFF switching	0-60
QS5-30A		30	10				
QS5-15N	I-O-I	15	5.5			Forward & reverse	60-0-60
QS5-30N		30	10				
QS5-15P/3	I-O-II	15	5.5			for 3 pole two circuit	60-0-60
QS5-30P/3		30	10				
QS5-63A	I-O	63	22	200000	180	ON-OFF switching	0-60
QS5-100A		100	30				
QS5-63N	I-O-I	63	22			Forward & reverse	60-0-60
QS5-100N		100	30				
QS5-63/P4	I-O-II	63	22			for 3 pole two circuit	60-0-60
QS5-100/P4		100					

