



4190

Application: It can be used for indicating the phase sequence and checking the open phase of three phase AC power

Features:

- *Wide measuring range for frequency (40Hz to 60Hz) and voltage (100V to 600V) in 3-phase AC power supply.
- *Phase sequence and open phase checking.
- *Open phase indication (LED and alarm).
- *Small size and light weight.

Specifications

Measuring Range	Frequency : 40Hz ~ 60Hz Voltage : 100V ~ 600V
Insulation Value	$\geq 50M\Omega$ (1000V)
Withstand Voltage	AC 2kV 50Hz 1min
Operating Temperature & Humidity	-10°C ~ +50°C ; < 85 % RH
Dimensions	115 mm (L) × 70 mm (W) × 40 mm (D)
Weight	≈ 300g